

# Moxi™ Kiss E

312 BTE receiver in canal (RIC)

## Signature features

6 channels

SmartFocus

Available within each manual program and is a fitter adjustable control for comfort or clarity

Natural Sound Balance

An adaptive feature to minimize artifacts that can occur when amplified sound combines in the ear canal with direct sound. Natural Sound Balance continuously monitors these sounds and makes precision adjustments to preserve a clear, balanced signal

Automatic Adaptation Manager

Allows for an automatic and smooth adjustment period for the patient; providing the best possible first fit acceptance combined with maximum long-term benefit for speech understanding

Feedback manager

Feedback manager offers maximum usable gain by suppressing feedback transients before they become audible


Wireless technology

DuoLink – adjustments conducted on one hearing instrument are automatically transferred to the other ear


## Additional features

- 4 manual programs
- Adaptive directional microphone
- AntiShock™
- MyMusic™
- Wind noise manager
- Speech enhancement LD
- Noise reduction
- Tinnitus masker
- Data logging
- Easy-t
- Optional remote control
- Optional wireless programming with iCube
- IntelliVent technology available on custom ear pieces


## Fitting guides



Moxi Kiss E  
(xS)



Moxi Kiss E  
power (xP)



Moxi Kiss E  
super power (xSP)

Moxi Kiss E is suitable for fitting mild to severe hearing losses and can fit audiogram configurations ranging from reverse to precipitously sloping.




# Moxi Kiss E RIC

Moxi Kiss E  
standard  
(xS receiver)




Moxi Kiss E  
power  
(xP receiver)

Moxi Kiss E  
super power  
(xSP receiver)

## ANSI 3.22 2009/IEC 118-7 2cc coupler technical data

Reference test frequency - IEC 118-7 (kHz)		1.6	1.6	1.6
				
OSPL90				
Maximum (dB SPL)		112	126	129
Nominal (dB SPL)		109	123	126
HFA-OSPL90 (dB SPL)		105	118	120
at RTF (dB SPL)		104	120	124
				
Full on gain (input 50 dB SPL)				
Maximum (dB)		45	55	61
HFA-FOG (dB)		39	48	55
at RTF (dB)		38	49	60
				
Reference test settings				
Frequency range (Hz)		<100-8300	<100-7300	<100-5500
Reference test gain (dB)		28	41	43
Current drain at RTS (mA)		1.15	1.25	1.2
Typical battery life (h)		141	130	135
Equivalent input noise at RTS (dB SPL)		19	18	19
Total harmonic distortion at 500 Hz/800 Hz/1600 Hz (%)		1.0/1.0/1.0	1.5/1.0/0.5	0.5/0.5/0.5
Electromagnetic compatibility				
EMC immunity by ANSI c63.19-2001 EMC, omni		M4	M4	M4

## IEC 118-o OES coupler technical data

Reference test frequency - IEC 118-o (kHz)		1.6	1.6	1.6
				
OSPL90				
Maximum (dB SPL)		121	132	133
at RTF (dB SPL)		113	129	132
				
Full on gain (input 50 dB SPL)				
Maximum (dB)		56	65	69
at RTF (dB)		46	58	68
				
Basic frequency response				
Frequency range (DIN 45605) (Hz)		<100-8600	<100-7500	<100-5800
Reference test gain (dB)		39	51	57
Current drain at RTG (mA)		1.15	1.2	1.2
Typical battery life (h)		141	135	135
Equivalent input noise at RTG (dB SPL)		19	18	19
Total harmonic distortion at 500 Hz/800 Hz/1600 Hz (%)		1.0/1.5/1.5	1.5/1.5/1.0	1.0/1.0/0.5
Electromagnetic compatibility				
EMC immunity by IEC 60118-13 2011 field strength 90/50/35 V/m, omni IRIL low/medium/high band (dB SPL)		37/25/47	37/25/47	37/25/47

## Legend

— Moxi Kiss E xS

— Moxi Kiss E xP

— Moxi Kiss E xSP

## Test conditions

Battery size: 312; Source: voltage 1.3 V

The measurements obtained with a closed configuration using an HA-1 coupler (ANSI-3.7-1995) or occluded ear simulator (EN 60711, coupling arrangement according to fig. 4 in the test standard). The hearing instrument set to Unitron Truefit test settings.

Domes should never be fit on patients with perforated eardrums, exposed middle ear cavities, or surgically altered ear canals.

In the case of such a condition, we recommend use of a customized earmold.

Sound pressure level of these hearing aids exceeds 132 dB SPL.

We reserve the right to change specification data without notice as improvements are introduced.